CLINTON Electronics *free ddns service setup for cricket dvrs*

for	Cricket	series	DVR
		00100	

Setting up DDNS		Using Internet Explorer:	
Follow the written instructions below, use images in the right hand column for reference.		Steps 1-4	System Braue (Prysk DONS) wat Tae Please select the preferable DDNS mode, then setup your DDNS server *Film CORS Use Hans, DDNS Possword, DDNS Host name, then press submit, truck concerned to DDNS Web * ex DDNS black that given windta com/ DDNS black that given windta com/
 After logging onto the DVR using Internet Explorer, click on the "Setup" button. 			DDNS Friends
2. Click on "DDNS" tab.			COMP Use News - Constrained -
3. Change DDNS Select to: http://www.no-ip.com.			CORS foot Name
4. Click on "Create Account".		0	No P Setting
 Create a username (4-16 characters) and click on "Check" to see if it is available. 		Steps 5-10	Vouche now creating a new account at www.no-ip.com for DDNS service Vouche now creating a new account at www.no-ip.com for DDNS service Vouche now creating in the provide service Vouche now creatin
6. Enter your e-mail address.			
7. Create a password (6-32 characters) and confirm password.			Manuar di duando in longiti Come Ressort (Para Cash (1111)
8. Enter your first name, last name, and postal code.			
9. Review the terms of service available at http://www.no-ip.com. Then check box next to "You agree to the TOS".		Stone	No.P Setting
10. Click on "Next".		11-13	
11. Create a desired hostname.			Hold Manuface Finandal Mathematics Finandal #: 1922 tild 2:10
12. Select "cedyn.com" from the list of domains.			
13. Click "Next".			Not
14. Account information will be displayed.		Ctopo	No P Setting
15. Click "OK".	L	Steps 14-15	
16. Information will be automatically entered into the DVR.			Account Hamation Usersame: dw1 E-Mai:::except@definedectorics.com FirdTerm::::dwn
 You may now connect to the DVR using the DDNS host name that you created. 			Larfane: Joh PostCoe: B111
Note : If the DVR is connected to a router, the HTTP port used in the DVR must be forwarded in the router to the DVR's IP address using TCP and UDP protocol.		Stope	
If the HTTP port has been changed from the default of 80, it must be entered after the DDNS host name with a colon : and then the port number.		16-18	System Bases (Myrc) 2005 [Mail Tate] Please stretche production COVS models then satep your COVIS server Face connects DONS Vision Planeteric COVIS FaceInterime, then press submit, Face connects DONS Vision Planeterimed COVIS FaceInterime, then press submit, Face Connects DONS Vision Planeterimed Covis FaceInterimed DONS Vision Planeterimed
Example: http://homedvr.cedyn.com:81			UCH s reversely and the second s
18. Click "Apply".			Votes sees: /// / / / / / / / / / / / / / / / / /

CLINTON Electronics

C

CRICKET

Clinton Electronics 6701 Clinton Road Loves Park, IL 61111 1.800.447.3306 **Sales** 1.800.549.6393 **Support** 1.815.633.8712 **Fax**

www.clintonelectronics.com v.01.21.11